


I hereby certify that this paper is being deposited with the United States Postal Service as Express Mail in an envelope addressed to: Asst. Comm. for Patents, Washington, D.C. 20231, on this date.

1/25/2002
Date


Express Mail Label No.:
EL846223125US

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT WE, Susumu Yoshida, a citizen of Japan residing at Kawasaki, Japan, Shuichi Hashimoto, a citizen of Japan residing at Kawasaki, Japan, Ryuki Kubohara, a citizen of Japan residing at Kawasaki, Japan, Tatsuhiko Kosugi, a citizen of Japan residing at Kawasaki, Japan, Takeyori Hara, a citizen of Japan residing at Kawasaki, Japan and Yoshiyuki Kagami, a citizen of Japan residing at Kawasaki, Japan have invented certain new and useful improvements in

RESONANCE-FREQUENCY MEASURING METHOD DETERMINING A RESONANCE FREQUENCY BY COUNTING THE NUMBER OF OFF-TRACK OCCURRENCES

of which the following is a specification : -

TITLE OF THE INVENTION

RESONANCE-FREQUENCY MEASURING METHOD
DETERMINING A RESONANCE FREQUENCY BY COUNTING THE
NUMBER OF OFF-TRACK OCCURRENCES

5

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention generally relates to
a resonance-frequency measuring method used for an
10 information recording and/or reproducing device, an
information recording and/or reproducing device, and
an electric filter, and, more particularly, to a
resonance-frequency measuring method for measuring a
resonance frequency of a mechanism unit of an
15 information recording and/or reproducing device
driven by the mechanism unit to record and/or
reproduce information, an information recording
and/or reproducing device, and an electric filter.

An information recording and/or
20 reproducing device, such as a hard disk drive, is
required to record and/or reproduce information at a
high speed with a high recording density. These
requirements raise a problem of head vibration due
to a resonance of a mechanism unit. In order to
25 repress a resonance component of the mechanism unit,
such an information recording and/or reproducing
device incorporates a notch filter for removing a
resonance component from a head-driving signal.
Since mechanism units of different devices have
30 different resonance frequencies, a cutoff frequency
of the notch filter needs to be set individually by
measuring a resonance frequency for each different
device. Therefore, an efficient method for
measuring a resonance frequency has been desired.

35

2. Description of the Related Art

First, a description will be given, with
reference to the drawings, of a hard disk drive.

FIG.1A is a cross-sectional view of a structure of a hard disk drive. FIG.1B is a plan view of the structure of the hard disk drive. FIG.2 is a block diagram of the hard disk drive.

5 A hard disk drive 1 mainly comprises a disk enclosure 11 and a circuit assembly 12. The disk enclosure 11 contains a magnetic disk 21, a spindle motor 22, a magnetic head 23, a head arm 24, a voice coil motor 25 (a mechanism unit), and a head
10 IC (Integrated Circuit) 26. The magnetic disk 21 is fixed to a rotating shaft of the spindle motor 22, and revolves in accordance with the rotation of the spindle motor 22.

15 The magnetic head 23 is arranged opposite the magnetic disk 21, and acts magnetically on the magnetic disk 21 so as to record and/or reproduce information. The magnetic head 23 is fixed on an end of the head arm 24. The head arm 24 is coupled with the voice coil motor 25 at the other end so as
20 to be revolved by the voice coil motor 25. Along with the revolution of the head arm 24, the magnetic head 23 moves in a radial direction of the magnetic disk 21.

25 The magnetic head 23 is connected to the head IC 26. The head IC 26 amplifies a signal that is to be recorded on the magnetic disk 21 by the magnetic head 23, and supplies the amplified signal to the magnetic head 23. The head IC 26 also
30 amplifies a reproduction signal that is reproduced from the magnetic disk 21 by the magnetic head 23, and supplies the amplified reproduction signal to the circuit assembly 12.

As shown in FIG.2, the circuit assembly 12 includes a read channel (RDC) 31, an MPU (Micro
35 Processing Unit) 32, a ROM (Read Only Memory) 33, a servo controller (SVC) 34 (an actuator; a driving unit), a hard disk controller (HDC) 35, a RAM

(Random Access Memory) 36, and an IDE (Integrated Device Electronics) connector 37.

The read channel 31 is connected with the head IC 26. The read channel 31 supplies a record
5 signal to the head IC 26, and also demodulates a reproduction signal amplified by the head IC 26 into reproduction data. The reproduction data demodulated by the read channel 31 is supplied to the HDC 35. The HDC 35 temporarily stores the
10 reproduction data in the RAM 36, and thereafter, supplies the reproduction data to a host computer (not shown in the figure) via the IDE connector 37.

Record data is supplied from the host computer to the IDE connector 37. The HDC 35
15 temporarily stores the record data in the RAM 36. Upon recording, the HDC 35 reads the record data from the RAM 36, and supplies the record data to the read channel 31. The read channel 31 modulates the record data so as to generate a record signal. The
20 record signal generated by the read channel 31 is supplied to the head IC 26. The head IC 26 amplifies the record signal, and supplies the amplified record signal to the magnetic head 23. The magnetic head 23 magnetizes the magnetic disk 21
25 by producing a magnetic field corresponding to the record signal so as to record the record signal on the magnetic disk 21.

In the above-mentioned course, the MPU 32 is supplied with the reproduction data demodulated
30 by the read channel 31. The MPU 32 reads a location signal (a present location signal) indicating an address on the magnetic disk 21 from the reproduction data, and performs a tracking servo control. The MPU 32 generates a control signal,
35 i.e., a tracking error signal, corresponding to a difference between the read location signal and a location signal (an aimed location signal)

representing a location where aimed information is recorded, and performs a notch-filter process to the generated control signal. Thereafter, the MPU 32 supplies the control signal to the servo controller 34. The notch-filter process removes a device's natural resonance frequency component from the control signal.

The servo controller 34 controls the voice coil motor 25 according to the control signal supplied from the MPU 32 so as to regulate a reading position of the magnetic head 23 reading a signal from the magnetic disk 21.

Thus, the magnetic head 23 can scan the aimed location on the magnetic disk 21 so as to obtain the aimed information.

In this course, the voice coil motor 25 exhibits a device-specific resonance frequency. Therefore, a firmware executed by the MPU 32 includes a resonance-frequency measuring process for measuring the device-specific resonance frequency so as to match a cutoff frequency in the notch-filter process to the device-specific resonance frequency.

FIG.3 is a functional block diagram of a conventional example of a tracking servo control system.

It is noted that a subtracter 41, a controller 42, a notch filter 43, an adder 44, a sine-wave disturbance generator 45, an FFT calculator 46, and an adjuster 47 are realized by the firmware as processes of the MPU 32.

The subtracter 41 is supplied with the aimed location signal and the present location signal, and calculates the difference between the aimed location signal and the present location signal so as to output difference information. The difference information is supplied to the controller 42. Based on the difference information supplied

from the subtracter 41, the controller 42 generates the control signal for controlling the voice coil motor 25.

5 The control signal generated by the
controller 42 is supplied to the notch filter 43. The notch filter 43 deducts a preset cutoff frequency component from the control signal. The control signal without the unnecessary component is supplied from the notch filter 43 to the adder 44.
10 The adder 44 adds a sine-wave disturbance signal supplied from the sine-wave disturbance generator 45 to the control signal supplied from the notch filter 43. The control signal including the sine-wave disturbance signal is supplied to the servo
15 controller 34.

Based on the control signal supplied from the adder 44, the servo controller 34 generates a driving signal for driving the voice coil motor 25. The driving signal generated by the servo controller
20 34 is supplied to the voice coil motor 25. The voice coil motor 25 is driven by the driving signal supplied from the servo controller 34 so as to alter a position of the magnetic head 23.

25 The magnetic head 23 reads a signal from the magnetic disk 21 at the altered position. This reproduction signal reproduced by the magnetic head 23 is supplied to the head IC 26. The head IC 26 amplifies the reproduction signal supplied from the magnetic head 23. The reproduction signal amplified
30 by the head IC 26 is supplied to the read channel 31. The read channel 31 demodulates the reproduction signal so as to obtain reproduction information. A location signal included in the reproduction information is supplied, as the present location
35 signal, to the subtracter 41 and the FFT (Fast Fourier Transform) calculator 46. The FFT calculator 46 performs an FFT process so as to

calculate amplitude of the location signal.

The amplitude of the location signal calculated in the FFT calculator 46 is supplied to the adjuster 47. The adjuster 47 detects a
5 frequency of the sine-wave disturbance signal generated by the sine-wave disturbance generator 45 that maximizes the calculation result, i.e., the amplitude of the location signal, of the FFT
10 calculator 46 by varying the frequency of the sine-wave disturbance signal and obtaining the calculation result of the FFT calculator 46. The adjuster 47 sets the detected maximizing frequency as the cutoff frequency in the notch filter 43.

Besides, in order to calculate the
15 amplitude of the location signal, a DFT (Discrete Fourier Transform Analysis) calculator and a Max-Min difference calculator are generally used in addition to the FFT calculator 46.

In measuring the resonance frequency in
20 the conventional hard disk drive, the resonance frequency is calculated by the FFT calculator 46, the DFT calculator and the Max-Min difference calculator. However, there have been problems, such as that the FFT calculation, the DFT calculation and
25 the Max-Min difference calculation are so complicated, and require large memory usage.

SUMMARY OF THE INVENTION

It is a general object of the present
30 invention to provide an improved and useful resonance-frequency measuring method and an electric filter in which the above-mentioned problems are eliminated.

A more specific object of the present
35 invention is to provide a resonance-frequency measuring method which can measure a resonance frequency with simple processes, and an electric

filter which can deal with varying resonance frequencies.

In order to achieve the above-mentioned objects, a resonance frequency of an information recording/reproducing device is measured by applying sine-wave oscillations at different frequencies one by one to the mechanism unit of the information recording/reproducing device reproducing information recorded on a medium by driving the mechanism unit, counting the number of times information reproduced upon application of each of the sine-wave oscillations differs from information indicating an aimed location, and determining the resonance frequency according to the number of times counted as above.

According to the present invention, since the resonance frequency can be determined by counting the number of off-track occurrences, complicated calculations, such as an FFT calculation, and a DFT calculation need not to be performed. Thus, programs of a smaller scale can realize this method with using only a smaller memory area storing those programs. Also, this method only requires a smaller work memory used upon executing the programs. Accordingly, the information recording/reproducing device needs to have only a small memory capacity.

Additionally, in the present invention, the sine-wave oscillations are applied to the mechanism unit by adding sine-wave signals at different frequencies one by one to a control signal controlling an actuator to drive the mechanism unit.

According to the present invention, the oscillations can be applied not directly to the mechanism unit, but in the form of signals, which can be realized by a simple structure.

In order to achieve the above-mentioned objects, there is also provided an electric filter

1005555555 01111111

comprising a plurality of notch filters combined so as to have a predetermined notch filter characteristic, the notch filters having different frequency characteristics.

5 Additionally, in the present invention, the notch filters may include:

 a first notch filter having a first cutoff frequency and exhibiting substantially symmetrical gain changes at frequencies below and above the
10 first cutoff frequency;

 a second notch filter having a second cutoff frequency lower than the first cutoff frequency, and exhibiting a smaller amount of gain changes and a smaller maximum gain at frequencies
15 below the second cutoff frequency than an amount of gain changes and a maximum gain at frequencies above the second cutoff frequency; and

 a third notch filter having a third cutoff frequency higher than the first cutoff frequency,
20 and exhibiting a larger amount of gain changes and a larger maximum gain at frequencies below the third cutoff frequency than an amount of gain changes and a maximum gain at frequencies above the third cutoff frequency.

25 According to the present invention, combining a plurality of notch filters having different frequency characteristics can extend a suppression frequency band in which gains are suppressed. In this structure, making gain changes
30 asymmetrical can extend the suppression frequency band without deteriorating the gain suppression.

 Other objects, features and advantages of the present invention will become more apparent from the following detailed description when read in
35 conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG.1A is a cross-sectional view of a structure of a hard disk drive;

FIG.1B is a plan view of the structure of the hard disk drive;

FIG.2 is a block diagram of the hard disk drive;

FIG.3 is a functional block diagram of a conventional example of a tracking servo control system;

FIG.4 is a functional block diagram of a tracking servo system according to an embodiment of the present invention;

FIG.5 is a flowchart of a notch filter setting process according to an embodiment of the present invention;

FIG.6 is an illustration used for explaining the notch filter setting process;

FIG.7A and FIG.7B show a frequency characteristic and a phase characteristic, respectively, of a notch filter according to an embodiment of the present invention, when a frequency band of the notch filter is varied;

FIG.8A and FIG.8B show a frequency characteristic and a phase characteristic of the notch filter, respectively, when a gain of the notch filter is varied;

FIG.9 is a block diagram of a variation of the notch filter;

FIG.10A and FIG.10B show a frequency-gain characteristic and a frequency-phase characteristic, respectively, when $N = 1$ in an expression representing a transfer function of a notch filter;

FIG.11A and FIG.11B show a frequency-gain characteristic and a frequency-phase characteristic, respectively, when $N = 1.33$;

FIG.12A and FIG.12B show a frequency-gain

10056865-012502

characteristic and a frequency-phase characteristic, respectively, when $N = 0.75$;

FIG.13A shows the frequency characteristics shown in FIG.10A, FIG.11A and
5 FIG.12A overlapped on one another;

FIG.13B shows the phase characteristics shown in FIG.10B, FIG.11B and FIG.12B overlapped on one another;

FIG.14A shows a synthesis of the frequency characteristics shown in FIG.10A, FIG.11A and
10 FIG.12A;

FIG.14B shows a synthesis of the phase characteristics shown in FIG.10B, FIG.11B and FIG.12B;

15 FIG.15A shows frequency characteristics of normal notch filters having different cutoff frequencies, overlapped on one another;

FIG.15B shows phase characteristics of the normal notch filters, overlapped on one another;

20 FIG.16A shows a synthesis of the frequency characteristics shown in FIG.15A; and

FIG.16B shows a synthesis of the phase characteristic shown in FIG.15B.

25 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Descriptions will now be given, with reference to the drawings, of embodiments according to the present invention.

First, a description will be given of a
30 resonance-frequency measuring method used for a hard disk drive (an information recording and/or reproducing device) according to an embodiment of the present invention.

The hard disk drive according to the
35 present embodiment has a similar structure to the structure of the conventional hard disk drive shown in FIG.1A to FIG.3, except for processes of a

10056865-012502

firmware stored in the ROM 33.

FIG.4 is a functional block diagram of a tracking servo system according to an embodiment of the present invention. Elements in FIG.4 that are identical to the elements shown in FIG.3 are referenced by the same reference marks, and will not be described in detail.

The tracking servo system of the hard disk drive according to the present embodiment comprises an off-track detector 101, an off-track scaler 102, and an adjuster 103, instead of the FFT calculator 46 and the adjuster 47 shown in FIG.3. The off-track detector 101, the off-track scaler 102, and the adjuster 103 form a measuring means. The adjuster 103 forms a resonance-frequency determining means and a filter adjusting means.

The off-track detector 101 is supplied with the aimed location signal from the HDC 35, and is also supplied with the present location signal from the read channel (RDC) 31. The off-track detector 101 compares the present location signal with the aimed location signal. When the present location signal derives from a track different from a track indicated by the aimed location signal, the off-track detector 101 judges that the present location is off-track, and supplies a pulse signal to the off-track scaler 102.

The off-track scaler 102 is a counter, which counts the pulse signal supplied from the off-track detector 101 during a predetermined scaling time. The off-track scaler 102 is cleared by the adjuster 103, and is provided with the scaling time by the adjuster 103. The adjuster 103 controls the entire system so as to determine the cutoff frequency used in the notch filter 43.

FIG.5 is a flowchart of a notch filter setting process according to an embodiment of the

present invention. FIG.6 is an illustration used for explaining the notch filter setting process.

The notch filter setting process is started upon the fulfillment of predetermined conditions, such as a reception of an externally supplied command, or internal errors occurring more than predetermined times.

First, in step S1-1 of the notch filter setting process, a measurement frequency f_s is set to a predetermined frequency f_a , and a recording sequence location x is initialized to "0" such that the magnetic head 23 is positioned on a predetermined track.

Next, in step S1-2, a sine-wave disturbance signal at the frequency f_s is produced, and is added to a tracking error signal.

Next, in step S1-3, the number of off-track occurrences is counted for a predetermined period of time. The off-track is a state in which the magnetic head 23 is displaced from a track on the magnetic disk 21, the track originally to be followed by the magnetic head 23. The off-track state is detected by demodulating a signal detected by the magnetic head 23 into demodulated information by the read channel 31, recognizing an address from the demodulated information, and judging whether or not the recognized address derives from the track mentioned in the step S1-1 on which the magnetic head 23 is positioned.

The number of off-track occurrences is counted up when the address recognized from the reproduced information does not derive from the track mentioned in the step S1-1.

Subsequently, in step S1-4, the number of off-track occurrences counted for the predetermined period of time in step S1-3 is stored in a measurement result sequence $res[x]$ preset in the MPU

32, or in a measurement result sequence $res[x]$ preset in the RAM 36. Then, in step S1-5, the measurement frequency f_s and the recording sequence location x are updated. The recording sequence
5 location x is updated to $(x + 1)$, for example. The measurement frequency f_s is updated to $(f_s + f_{step})$, for example. In this expression, f_s represents the present measurement frequency, and f_{step} represents a predetermined step frequency. That is, in this
10 updating step, the measurement frequency f_s is set to a frequency obtained by adding the step frequency f_{step} to the present measurement frequency.

Subsequently, in step S1-6, it is judged whether or not the updated measurement frequency f_s
15 exceeds a predetermined upper-limit frequency f_b .

When it is judged in the step S1-6 that the updated measurement frequency f_s is lower than the predetermined upper-limit frequency f_b , the steps S1-2 to S1-5 are performed. When it is judged
20 in the step S1-6 that the updated measurement frequency f_s is higher than the predetermined upper-limit frequency f_b , step S1-7 is performed. In the step S1-7, a largest number of off-track occurrences is obtained from among the numbers of off-track
25 occurrences stored in the measurement result sequences $res[0]$ to $res[(n-1)]$, and a measurement frequency f_t associated with the measurement result sequence $res[x]$ (x = the recording sequence location) storing the largest number of off-track
30 occurrences is obtained. It is noted that n in $res[(n-1)]$ corresponds to the number of times the measurement frequency is updated.

FIG.6 shows the relation between the measurement frequency f_s and the number of off-track
35 occurrences. As shown in FIG.6, a plurality of peaks p_1 to p_4 are exhibited. By referring to these peaks, the measurement frequency f_t corresponding to

10056865-012502

the largest number of off-track occurrences is obtained, and is set as the cutoff frequency used in the notch filter 43.

In step S1-8, a filter coefficient used to obtain a notch filter characteristic is calculated. The notch filter characteristic exhibits the measurement frequency f_t as a center frequency.

Subsequently, in step S1-9, a filter coefficient presently set in the ROM 33 is changed to the filter coefficient calculated in the step S1-8.

The notch filter 43 is formed by a digital filter realized by processes of the MPU 32. A transfer function of a digital notch filter is generally represented by the following expression.

$$G(s) = (s^2 + 2D_p Z_t \Omega_c s + \Omega_c^2) / (s^2 + 2Z_t \Omega_c s + \Omega_c^2) \dots (1)$$

Ω_c : a cutoff value

Z_t : a spread function

D_p : a depth function

FIG.7A and FIG.7B show a frequency characteristic and a phase characteristic of the notch filter, respectively, when a frequency band of the notch filter is varied. FIG.8A and FIG.8B show a frequency characteristic and a phase characteristic of the notch filter, respectively, when a gain of the notch filter is varied.

The transfer function $G(s)$ represented by the expression (1) has the characteristics of the notch filter as shown in FIG.7A and FIG.8A.

Increasing the value of the function Z_t in the expression (1) spreads the frequency band, as shown in FIG.7A. Decreasing the value of the function D_p in the expression (1) deepens the gain, as shown in FIG.8A.

Additionally, increasing the cutoff value Ω_c in the expression (1) increases the cutoff frequency f_c . Decreasing the cutoff value Ω_c

10056855-04502

decreases the cutoff frequency f_c .

The MPU 32 can set the above-mentioned cutoff value Ω_c in the ROM 33 as a parameter. In the above-mentioned step S1-9, the cutoff value Ω_c set in the ROM 33 is changed such that the cutoff frequency f_c equals the measurement frequency f_t corresponding to the largest number of off-track occurrences.

For example, the cutoff value Ω_c is in relation to the cutoff frequency f_c as follows.

$\Omega_c = 2\pi f_c$ (π : the ratio of the circumference of a circle to its diameter; f_c : the cutoff frequency)

Accordingly, the cutoff value Ω_c is so set that the cutoff frequency f_c equals the measurement frequency f_t corresponding to the largest number of off-track occurrences.

In the present embodiment, the off-track state is detected when the present location address is different from the aimed location address. However, the off-track state may be detected when the tracking error signal is larger than a predetermined amount.

According to the present embodiment, by varying the frequency of the sine-wave disturbance signal and counting the number of off-track occurrences for a predetermined period of time for each varied frequency, a frequency maximizing the number of off-track occurrences is set as a resonance frequency (corresponding to the cutoff frequency). Thus, in the present embodiment, the resonance frequency can be obtained by simpler processes with smaller memory usage than conventional calculations, such as the FFT calculation, the DFT calculation, and the Max-Min difference calculation.

Additionally, in the present embodiment,

the cutoff frequency f_c may be set in the notch filter 43 not only upon shipping the hard disk drive, but also may be reset upon starting the hard disk drive after the shipping, or when an error rate or
5 the number of retries exceeds a predetermined value.

Besides, as described above, the present embodiment employs a normal digital notch filter represented by the expression (1) as the notch filter 43. However, the normal notch filter has a
10 narrow suppression band. Accordingly, in cases that a mechanical resonance frequency of the information recording and/or reproducing device (the hard disk drive) differs from the cutoff frequency of the notch filter, an uncontrollable oscillation arises
15 when the differing mechanical resonance frequency occurs. Therefore, a digital notch filter having an extended suppression band may be employed as the notch filter 43.

FIG.9 is a block diagram of a variation of
20 the notch filter according to the above-described embodiment of the present invention.

A notch filter 200 according to the present variation comprises four notch filters 201 to 204. The notch filter 201 corresponds to a
25 fourth notch filter. The notch filter 202 corresponds to a second notch filter. The notch filter 203 corresponds to a first notch filter. The notch filter 204 corresponds to a third notch filter.

The control signal supplied from the
30 controller 42 is filtered through the notch filters 201 to 204 in series. Thereby, the control signal supplied from the controller 42 is subjected to the same process as when the control signal is filtered through one notch filter having one frequency
35 characteristic equivalent to a synthesis of frequency characteristics of the notch filters 201 to 204.

The notch filter 201 has a normal filter characteristic with the cutoff frequency being f_1 .

The transfer function of a normal notch filter is represented by the foregoing expression

5 (1).

The expression (1) can be z-transformed into the following expression (2).

$$G(z) = [(1 + 2D_p Z_t A + A^2) + 2(A^2 - 1)Z^{-1} + (1 - 2D_p Z_t A + A^2)Z^{-2}] / [(1 + 2Z_t A + A^2) + 2(A^2 - 1)Z^{-1} + (1 - 2Z_t A + A^2)Z^{-2}]$$

10 ... (2)

In the present variation, the expression (1) is changed to the following expression (3).

$$G(s) = (s^2 + 2D_p Z_t \Omega_c s + \Omega_c^2) / (ns^2 + 2Z_t \Omega_c s + \Omega_c^2) \dots (3)$$

15 In the expression (3), when s becomes larger, i.e., when the frequency becomes higher, terms other than s^2 become ignorable. Accordingly, the expression (3) can be expressed as follows.

$$G(s) = 1/n \dots (4)$$

20 From this expression (4), it is understood that the gain of the notch filter can be varied by changing n .

The expression (3) can be z-transformed into the following expression (5).

$$G(z) = [(1 + 2D_p Z_t A + A^2) + 2(A^2 - 1)Z^{-1} + (1 - 2D_p Z_t A + A^2)Z^{-2}] / [(N + 2Z_t A + A^2) + 2(A^2 - N)Z^{-1} + (N - 2Z_t A + A^2)Z^{-2}]$$

25 ... (5)

Besides, the notch filter 201 has a transfer function obtained by substituting "1" for N in the expression (5).

30 FIG.10A and FIG.10B show filter characteristics when $N = 1$. FIG.10A shows a frequency-gain characteristic. FIG.10B shows a frequency-phase characteristic.

35 The notch filter 201 exhibits a symmetrical form with a center frequency at the center, as indicated by a broken line in FIG.10A. The cutoff frequency of the notch filter 201 is set

to f_1 .

The control signal filtered through the notch filter 201 is supplied to the notch filter 202. The notch filter 202 has a transfer function
5 obtained by substituting "1.33" for N in the expression (5).

FIG.11A and FIG.11B show filter characteristics when $N = 1.33$. FIG.11A shows a frequency-gain characteristic. FIG.11B shows a
10 frequency-phase characteristic.

The cutoff frequency of the notch filter 202 is set to f_2 . As shown in FIG.11A, the notch filter 202 exhibits a larger gain at frequencies below the cutoff frequency f_2 than at frequencies
15 above the cutoff frequency f_2 . The cutoff frequency f_2 is higher than the cutoff frequency f_1 .

The control signal filtered through the notch filter 202 is supplied to the notch filter 203. The notch filter 203 has a transfer function
20 obtained by substituting "1" for N in the expression (5). The notch filter 203 has characteristics indicated by solid lines in FIG.10A and FIG.10B. The cutoff frequency of the notch filter 203 is set to f_3 . The cutoff frequency f_3 is higher than the
25 cutoff frequency f_2 . For example, the cutoff frequency f_3 is set to the resonance frequency obtained as described above.

The control signal filtered through the notch filter 203 is supplied to the notch filter 204.
30 The notch filter 204 has a transfer function obtained by substituting "0.75" for N in the expression (5).

FIG.12A and FIG.12B show filter characteristics when $N = 0.75$. FIG.12A shows a frequency-gain characteristic. FIG.12B shows a
35 frequency-phase characteristic.

The cutoff frequency of the notch filter

204 is set to f_4 . As shown in FIG.12A, the notch filter 204 exhibits a larger gain at frequencies above the cutoff frequency f_4 than at frequencies below the cutoff frequency f_4 . The cutoff frequency f_4 is higher than the cutoff frequency f_3 .

FIG.13A shows the frequency characteristics of the notch filters 201 to 204 overlapped on one another. FIG.13B shows the phase characteristics of the notch filters 201 to 204 overlapped on one another. FIG.14A shows a synthesis of the frequency characteristics of the notch filters 201 to 204. FIG.14B shows a synthesis of the phase characteristics of the notch filters 201 to 204.

Synthesizing the frequency characteristics of the notch filters 201 to 204 shown in FIG.13A forms the characteristic shown in FIG.14A. As shown in FIG.14A, a sufficiently large attenuation of substantially 30 dB can be obtained in a wide frequency band ranging from the frequency f_2 to the frequency f_4 .

Also, due to the frequency characteristic of the notch filter 201, a quality factor Q can be relaxed at low frequencies so as to realize an attenuation in the wide frequency band extended to the low frequencies.

FIG.15A to FIG.16B are graphs used for explaining characteristics synthesized from characteristics of normal notch filters having different frequencies. FIG.15A shows the frequency characteristic of the normal notch filter 201 having the cutoff frequency f_1 and the transfer function obtained by substituting "1" for N in the expression (5), a frequency characteristic of the notch filter 202 having the cutoff frequency f_2 and the transfer function obtained by substituting "1" for N in the expression (5), a frequency characteristic of the

notch filter 203 having the cutoff frequency f_3 and the transfer function obtained by substituting "1" for N in the expression (5), and a frequency characteristic of the notch filter 204 having the cutoff frequency f_4 and the transfer function obtained by substituting "1" for N in the expression (5). In FIG.15A, these four frequency characteristics are overlapped on one another. FIG.15B shows the phase characteristic of the normal notch filter 201 having the cutoff frequency f_1 and the transfer function obtained by substituting "1" for N in the expression (5), a phase characteristic of the notch filter 202 having the cutoff frequency f_2 and the transfer function obtained by substituting "1" for N in the expression (5), a phase characteristic of the notch filter 203 having the cutoff frequency f_3 and the transfer function obtained by substituting "1" for N in the expression (5), and a phase characteristic of the notch filter 204 having the cutoff frequency f_4 and the transfer function obtained by substituting "1" for N in the expression (5). In FIG.15B, these four phase characteristics are overlapped on one another.

FIG.16A shows a synthesis of the frequency characteristic of the notch filter 201 having the cutoff frequency f_1 and the transfer function obtained by substituting "1" for N in the expression (5), the frequency characteristic of the notch filter 202 having the cutoff frequency f_2 and the transfer function obtained by substituting "1" for N in the expression (5), the frequency characteristic of the notch filter 203 having the cutoff frequency f_3 and the transfer function obtained by substituting "1" for N in the expression (5), and the frequency characteristic of the notch filter 204 having the cutoff frequency f_4 and the transfer function obtained by substituting "1" for N in the

expression (5). FIG.16B shows a synthesis of the phase characteristic of the notch filter 201 having the cutoff frequency f_1 and the transfer function obtained by substituting "1" for N in the expression (5), the phase characteristic of the notch filter 202 having the cutoff frequency f_2 and the transfer function obtained by substituting "1" for N in the expression (5), the phase characteristic of the notch filter 203 having the cutoff frequency f_3 and the transfer function obtained by substituting "1" for N in the expression (5), and the phase characteristic of the notch filter 204 having the cutoff frequency f_4 and the transfer function obtained by substituting "1" for N in the expression (5).

When the frequency characteristics shown in FIG.15A are synthesized as shown in FIG.16A, gains at the cutoff frequencies f_1 to f_4 are not very large being approximately 20 dB. However, according to the present variation, the notch filters 201 and 203 are combined with the notch filters 202 and 204 exhibiting asymmetrical gain changes on opposite sides of the cutoff frequency f_2/f_4 . Thereby, sufficiently deep gains of 30 dB can be achieved at the cutoff frequencies f_1 to f_4 . In addition, according to the present variation, the phase characteristic shown in FIG.14B is substantially the same as shown in FIG.16B.

As described above, according to the present variation, even when the frequency band of the notch filter is extended, the deep gains can be obtained. Therefore, even when the resonance frequency differs from the cutoff frequency, the resonance frequency component can be surely removed.

In the present variation, the cutoff frequency f_3 of the notch filter 203 is set to the resonance frequency measured in the above-described

notch filter setting process shown in FIG.5.

However, the cutoff frequency f_2 of the notch filter 202 may be set to the above-mentioned resonance frequency. Furthermore, the cutoff frequency f_2 of the notch filter 202 and the cutoff frequency f_3 of the notch filter 203 may be set such that a frequency therebetween becomes the above-mentioned resonance frequency. That is, the cutoff frequencies may be so set as to easily deal with the differing resonance frequency.

Additionally, since the notch filter 200 according to the present variation has a wide frequency band of attenuation, the notch filter 200 is also able to cut out the resonance frequency component from the control signal simply by setting the cutoff frequency of the notch filter to the resonance frequency measured beforehand, without measuring a resonance frequency for each different device and matching the cutoff frequency to the measured resonance frequency of each different device.

In addition, although the above-described embodiments set forth the hard disk drive provided with the resonance-frequency measuring method and the electric filter according to the present invention, embodiments of the present invention are not limited to the hard disk drive; the present invention is also applicable to other devices, such as an optical disk device and a tape device. Further, the present invention is applicable to a device in general which reproduces information recorded on a medium by a mechanism unit thereof.

The present invention is not limited to the specifically disclosed embodiments, and variations and modifications may be made without departing from the scope of the present invention.

The present application is based on

Japanese priority application No. 2001-278612 filed on September 13, 2001, the entire contents of which are hereby incorporated by reference.

10390 10391 10392 10393 10394 10395 10396 10397 10398 10399 10400 10401 10402 10403 10404 10405 10406 10407 10408 10409 10410 10411 10412 10413 10414 10415 10416 10417 10418 10419 10420 10421 10422 10423 10424 10425 10426 10427 10428 10429 10430 10431 10432 10433 10434 10435 10436 10437 10438 10439 10440 10441 10442 10443 10444 10445 10446 10447 10448 10449 10450 10451 10452 10453 10454 10455 10456 10457 10458 10459 10460 10461 10462 10463 10464 10465 10466 10467 10468 10469 10470 10471 10472 10473 10474 10475 10476 10477 10478 10479 10480 10481 10482 10483 10484 10485 10486 10487 10488 10489 10490 10491 10492 10493 10494 10495 10496 10497 10498 10499 10500 10501 10502 10503 10504 10505 10506 10507 10508 10509 10510 10511 10512 10513 10514 10515 10516 10517 10518 10519 10520 10521 10522 10523 10524 10525 10526 10527 10528 10529 10530 10531 10532 10533 10534 10535 10536 10537 10538 10539 10540 10541 10542 10543 10544 10545 10546 10547 10548 10549 10550 10551 10552 10553 10554 10555 10556 10557 10558 10559 10560 10561 10562 10563 10564 10565 10566 10567 10568 10569 10570 10571 10572 10573 10574 10575 10576 10577 10578 10579 10580 10581 10582 10583 10584 10585 10586 10587 10588 10589 10590 10591 10592 10593 10594 10595 10596 10597 10598 10599 10600 10601 10602 10603 10604 10605 10606 10607 10608 10609 10610 10611 10612 10613 10614 10615 10616 10617 10618 10619 10620 10621 10622 10623 10624 10625 10626 10627 10628 10629 10630 10631 10632 10633 10634 10635 10636 10637 10638 10639 10640 10641 10642 10643 10644 10645 10646 10647 10648 10649 10650 10651 10652 10653 10654 10655 10656 10657 10658 10659 10660 10661 10662 10663 10664 10665 10666 10667 10668 10669 10670 10671 10672 10673 10674 10675 10676 10677 10678 10679 10680 10681 10682 10683 10684 10685 10686 10687 10688 10689 10690 10691 10692 10693 10694 10695 10696 10697 10698 10699 10700 10701 10702 10703 10704 10705 10706 10707 10708 10709 10710 10711 10712 10713 10714 10715 10716 10717 10718 10719 10720 10721 10722 10723 10724 10725 10726 10727 10728 10729 10730 10731 10732 10733 10734 10735 10736 10737 10738 10739 10740 10741 10742 10743 10744 10745 10746 10747 10748 10749 10750 10751 10752 10753 10754 10755 10756 10757 10758 10759 10760 10761 10762 10763 10764 10765 10766 10767 10768 10769 10770 10771 10772 10773 10774 10775 10776 10777 10778 10779 10780 10781 10782 10783 10784 10785 10786 10787 10788 10789 10790 10791 10792 10793 10794 10795 10796 10797 10798 10799 10800 10801 10802 10803 10804 10805 10806 10807 10808 10809 10810 10811 10812 10813 10814 10815 10816 10817 10818 10819 10820 10821 10822 10823 10824 10825 10826 10827 10828 10829 10830 10831 10832 10833 10834 10835 10836 10837 10838 10839 10840 10841 10842 10843 10844 10845 10846 10847 10848 10849 10850 10851 10852 10853 10854 10855 10856 10857 10858 10859 10860 10861 10862 10863 10864 10865 10866 10867 10868 10869 10870 10871 10872 10873 10874 10875 10876 10877 10878 10879 10880 10881 10882 10883 10884 10885 10886 10887 10888 10889 10890 10891 10892 10893 10894 10895 10896 10897 10898 10899 10900 10901 10902 10903 10904 10905 10906 10907 10908 10909 10910 10911 10912 10913 10914 10915 10916 10917 10918 10919 10920 10921 10922 10923 10924 10925 10926 10927 10928 10929 10930 10931 10932 10933 10934 10935 10936 10937 10938 10939 10940 10941 10942 10943 10944 10945 10946 10947 10948 10949 10950 10951 10952 10953 10954 10955 10956 10957 10958 10959 10960 10961 10962 10963 10964 10965 10966 10967 10968 10969 10970 10971 10972 10973 10974 10975 10976 10977 10978 10979 10980 10981 10982 10983 10984 10985 10986 10987 10988 10989 10990 10991 10992 10993 10994 10995 10996 10997 10998 10999 11000 11001 11002 11003 11004 11005 11006 11007 11008 11009 11010 11011 11012 11013 11014 11015 11016 11017 11018 11019 11020 11021 11022 11023 11024 11025 11026 11027 11028 11029 11030 11031 11032 11033 11034 11035 11036 11037 11038 11039 11040 11041 11042 11043 11044 11045 11046 11047 11048 11049 11050 11051 11052 11053 11054 11055 11056 11057 11058 11059 11060 11061 11062 11063 11064 11065 11066 11067 11068 11069 11070 11071